

### Feedforward and repetitive control of a servo piezo-mechanical hydraulic actuator Mercorelli, Paolo

Published in: Journal of Physics: Conference Series

DOI: 10.1088/1742-6596/1564/1/012005

Publication date: 2020

**Document Version** Publisher's PDF, also known as Version of record

Link to publication

Citation for pulished version (APA): Mercorelli, P. (2020). Feedforward and repetitive control of a servo piezo-mechanical hydraulic actuator. Journal of Physics: Conference Series, 1564, Article 012005. https://doi.org/10.1088/1742-6596/1564/1/012005

#### **General rights**

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
  You may freely distribute the URL identifying the publication in the public portal ?

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

#### **PAPER • OPEN ACCESS**

# Feedforward and repetitive control of a servo piezo-mechanical hydraulic actuator

To cite this article: Paolo Mercorelli 2020 J. Phys.: Conf. Ser. 1564 012005

View the article online for updates and enhancements.

#### You may also like

- Performance Comparison of the Electrolytic Cells Having Different Configurations for the Production of HCI and NaOH from Brine Jaewon Kim, Ki Bong Lee, Woojoo No et al.
- <u>Performance Comparison of the</u> <u>Electrolytic Cells Having Different</u> <u>Configurations for the Production of HCI</u> and NaOH from NaCI Jaewon Kim, Saleem Abbas, Ki Bong Lee et al.
- Development of a uni-axial hybrid actuator using the combination of an air actuator and a giant-magnetostrictive actuator Yoshiya Nakamura, Masanao Nakayama, Keiji Masuda et al.



This content was downloaded from IP address 193.174.36.131 on 27/04/2022 at 09:55

## Feedforward and repetitive control of a servo piezo-mechanical hydraulic actuator

#### Paolo Mercorelli

Institute of Product and Process Innovation, Leuphana University of Lueneburg, Universitaetsallee 1, D-21335 Lueneburg, Germany

1564 (2020) 012005

E-mail: mercorelli@uni.leuphana.de

Abstract. In this paper a hybrid actuator is proposed. The hybrid actuator consists of a piezo-mechanical structure and a hydraulic ratio displacement. Particular attention is paid to a liquid spring model of the displacement ratio which represents the hydraulic part of the mechanism to control an intake and exhaust valve of a combustion engine. The whole mechanism is controlled using a cascade repetitive control to track a periodic signal combined with a proportional derivative (PD) regulator and a feedforward action. Measured results are shown.

#### 1. Model of the hybrid actuator

In this part of the paper the model of the actuator is presented. The actuator consists of different technical parts: a piezo-electric structure, a servo-piston and a hydraulic structure.

#### 1.1. Piezo-electric structure

The mathematical model is the same which is adopted in [1], [2] and in [3]. The proposed sandwich model and the corresponding circuit are presented in Fig. 1. The details on this model can be found in [4]. Considering the whole system described in Fig. 1 with the assumption of compressibility of the oil, the whole mechanical system can be represented by a spring mass structure as shown in the conceptual scheme of Fig. 1. Concerning the piezo actuator, observing Fig. 1, K and D represent the elasticity and the friction constant of the spring which is antagonist to the piezo effect and is incorporated in the PEA. In the technical literature, factor  $D_x K_x = T_{em}$ is known with the name "transformer ratio" and states that the most important characteristic of the electromechanical transducer in which  $K_x$  is the elasticity constant factor of the PEA and  $D_x$  is the parameter which is responsible to transform voltage into movement. In fact, another well-known physical relation is  $F_z(t) = D_x K_x V_z(t)$  which represents the piezo force in which  $V_z$ is the internal voltage. In the ideal case, we have that  $V_z(t) = V_{in}(t)$  where  $V_{in}(t)$  states the input voltage. According to [4], in Fig. 1 a possible model representation of a piezo actuator is reported.

Content from this work may be used under the terms of the Creative Commons Attribution 3.0 licence. Any further distribution of this work must maintain attribution to the author(s) and the title of the work, journal citation and DOI. Published under licence by IOP Publishing Ltd 1



Figure 1. Scheme of the electrical part of the piezo actuator. Mass spring model of the piezo servo piston actuator

#### 1.2. Servo piston structure

The displacement ratio is calculated considering the surface quotient between the piezo (radius = 40mm) and the servo piston (radius = 4mm):

$$i_{Weg} = \frac{A_1}{A_2}.\tag{1}$$

The oil compressibility is comparable with Hook's law of the material technique [5]. In [5] the concept of a liquid spring is introduced and the fluid compressibility is modelled using an elasticity factor. Considering [5], the coefficient of the liquid spring coefficient  $Ko_{FL}$  in a pressure form is calculated using the following expression:

$$Ko_{FL} = \frac{V_0}{\Delta V(t)} \Delta p(t), \tag{2}$$

in which  $V_0$  represents the total volume in the chamber.  $\Delta V(t)$  is the compressed volume because of the acting force which generates a pressure difference equal to  $\Delta p(t)$ , see [5]. As shown in Fig. 1, two surfaces  $A_1$  and  $A_2$  play a role in the hydraulic ratio displacement. This ratio states the steady-state gain position factor of this part of the actuator. From Fig. 1 it is possible to observe that the model consists of two hydraulic cylinders. The forces at the connecting surfaces of both cylinders are calculated through the following product:

$$F_{A1}(t) = A_{F1} K o_{FL1} x_1(t) = \frac{A_1}{A_1 + A_2} K o_{FL1} x_1(t),$$
(3)

and

$$F_{A2}(t) = A_{F2} K o_{FL2} x_2(t) = \frac{A_2}{A_1 + A_2} K o_{FL2} x_2(t).$$
(4)

#### 1.3. Hydraulic structure

For constant pressures, the volumetric flow  $Q_{th}(t)$  of the value drive is proportional to the length of the opening slit that equals  $x_2(t) - \overline{x}_2$ . Considering

$$Q_{th}(t) = (x_2(t) - \overline{x}_2(t)) K_{SP}$$
(5)

with  $K_{SP}$  which represents a parameter depending on the pressure and  $\overline{x}_2(t)$  represents the initial servo piston position at which corresponds a  $Q_{th}(t) = 0$ . In Fig. 2 the whole actuator and a possible model of its hydraulic part are shown as proposed in [5]. The model was presented in [5] but in a linear approximation form which is very often used in industrial applications.



Figure 2. Scheme of the whole actuator. Block diagram structure of the hydraulic part of the actuator

$$\dot{x}_V(t) = K_H Q_{th}(t),\tag{6}$$

where  $\dot{x}_V(t)$  represents the velocity of the value and  $Q_{th}(t)$  the volumetric flow.  $K_H$  represents a physical constant which does not depend on the pressure p(t) and according to [5] it is expressed as follows:

$$K_{H} = \frac{V_{H}V_{M}A_{VP}}{1 + V_{H}V_{M}A_{VP}(A_{VP} + A_{L})},$$
(7)

where, according to Fig. 2,  $V_H$  is the steady-state parameter between p(t) and  $\tilde{Q}_{th}(t) - Q_{th}(t)$ and  $V_H$  is the steady-state parameter between force and the velocity of the valve. More in depth,  $K_H$  represents the closed loop steady-state gain of the scheme of Fig. 2, see [5]. Equation (6) states the steady state condition of the hydraulic valve system. In fact, Eq. (7) represents the steady state constant of the linear system proposed in [5] as a simplified model of the hydraulic valve system which consists of a transfer function between variables  $Q_{th}(t)$  and  $x_V(t)$ .

#### 2. Control strategy

In Fig. 3 the adopted control scheme is shown. The control scheme presents a feedforward action to compensate the steady state error because of the absence of the integral action in the controller. Together with the feedforward action a repetitive control algorithm is used because of the presence of a periodic signal to be tracked. It is known that the control loop can need to be stabilised and therefore, a stabilising PD controller is considered in the loop.

#### 2.1. Feed-forward control

Thanks to modelling approximations described above, the inversion of the system described in Eq. (6) is as follows:

$$Q_{th}(t) = K_H^{-1} \dot{x}_{V_d}(t), \tag{8}$$

in which  $\dot{x}_{V_d}(t)$  represents the desired velocity of the value. The next step is to invert Eq. (5):

$$x_2(t) = K_{SP}^{-1}Q_{th}(t) + \overline{x}_2.$$
(9)

1564 (2020) 012005 doi:10.1088/1742-6596/1564/1/012005



Figure 3. Block diagram of the control structure

The steady-state feedforward control can be summarized as follows: being  $F_z(t) = F_{A1}(t) = D_x K_x V_{inff}(t)$  and  $p(t) = \frac{F_{A2}(t)}{A2} = \frac{F_{A1}(t)}{A1}$ , then  $F_{A2}(t) = \frac{A_2}{A_1} F_z(t)$  and considering Eq. (4), then  $A_{F2} K_{FL2} x_2(t) = \frac{A_2}{A_1} D_x K_x V_{inff}(t)$ . It is straightforward to obtain the following relation:

$$V_{inff}(t) = \frac{A_{F2}K_{FL2}(K_{SP}^{-1}K_{H}^{-1}\dot{x}_{Vd}(t) + \overline{x}_{2})}{\frac{A_{2}}{A_{1}}D_{x}K_{x}}.$$
(10)

#### 3. Experimental results using repetitive control

According to the standard control scheme represented in Fig. 3 some measurements were done. It is known that a repetitive controller is characterised by the following transfer function:

$$G_r(s) = \frac{1}{1 - e^{-T_p s}}.$$
(11)

Parameter  $T_p$  represents the period of the periodical signal to be tracked. Figure 3 shows also another controller in the loop which is necessary to stabilise the control loop. Normally, the repetitive controller is realised using a discrete technique and Eq. (11) becomes as follows:

$$G_r(z) = \frac{1}{1 - z^{-T_p}}.$$
(12)

Figure 4 shows a detail of the piezo position and a corresponding detail of the servo piston position with 5000 cycles per minute. Figure 5 shows the measured results of pressure inside the stroke ratio and the position measurements. A detailed scheme of the repetitive control idea is shown in Fig. 3. Measured results in an experimental setup using a dSPACE system to implement the control structure confirm that the control scheme described in Fig. 3 can be used as an effective feedforward control for the presented hybrid actuator.

#### 4. Conclusion and outlook

The paper deals with modelling and control of a hybrid actuator. Particular attention is paid to a hydraulic spring model of the ratio displacement which represents the hydraulic part of the mechanism. A repetitive controller is applied to track a periodical signal together with a PD-controller which is devoted to stabilise the feedback control loop. Measured results are presented to demonstrate the effectiveness of the proposed method. Future advancements of this work can include a detailed friction model of the mechanical system and its control using Sliding Mode Control as proposed in [6] and in [7]. Moreover, in order to reduce the number of sensors an implementation of a Kalman Filter can be considered as proposed in [8].



Figure 4. Detail of the piezo position and corresponding detail of the servo piston position with 5000 cycles per minute



Figure 5. Oil chamber pressure and valve position with 5000 cycles per minute

#### Acknowledgment

The author wants to acknowledge Lucas Köhler, Guido Bergholz and Robert Zylla of Ostfalia University of Applied Sciences for the collaboration in doing the measurements. The paper could not be accomplished without them.

#### References

- P. Mercorelli and N. Werner A model of a servo piezo mechanical hydraulic actuator and its regulation using repetitive control In 2014 IEEE/ASME International Conference on Advanced Intelligent Mechatronics, Besacon, France, 2014
- [2] Mercorelli, P. and Werner, N., An adaptive resonance regulator design for motion control of intake valves in camless engine systems. In *IEEE Trans. on Ind. Electron.*, 64, (4): 3413-3422, 2017.
- [3] P. Mercorelli and N. Werner. A hybrid actuator modelling and hysteresis effect identification in camless internal combustion engines control. In *International Journal of Modelling, Identification and Control*, 21(3):253–263, 2014.
- [4] Y.-C. Yu and M.-K. Lee. A dynamic nonlinearity model for a piezo-actuated positioning system. In Proceedings of the 2005 IEEE International Conference on Mechatronics, ICM 10<sup>th</sup>-12<sup>th</sup> July, Taipei, 2005.
   [5] H. Murrenhoff. In Servohydraulik. Shaker Verlag, Aachen, 2002.
- [6] T. Ferch and P. Mercorelli. Vertical Dynamics Description and its Control in the Presence of Nonlinear Friction. In WSEAS Transactions on Systems, 18:198–212, 2019.
- [7] K.-C. Schwab and L. Schräder and P. Mercorelli and J.T. Lassen. Sliding Mode and Model Predictive Control for Inverse Pendulum. In WSEAS Transactions on Systems and Control, 14:190–195, 2019.
- [8] J.T. Lassen, P. Mercorelli. Tuning Kalman Filter in Linear Systems. In WSEAS Transactions on Systems and Control, 14:209–212, 2019.